

Tester SICO 2062 FMX

SICO 2062 FMX

Now available!

Meter for FMX 2-line control units (SbL 60)

Device for selective voltage measurements

Data

Measuring ranges:
- Selective alternating voltage /
frequencies to be set:
305 | 370 | 450 | 550 | 675 | 825 | ... | 5060 Hz - FMX 2
2.04 | 2.52 | 2.53 | 4.15 | 5.06 kHz - Sk 11 / AZL
- Broad-band voltage measurement
- Direct voltage
- Frequency

Input resistance: >/= 1 MegaOhm
Display: LCD with backlighting
Measuring error: Operating temperature range: -40°C to 70°C
Power supply: 1 accu Li-Ion or 3 batteries 1.5 V or rechargeable batteries 1.2 V
IP code: IP 54
Dimensions with handle (WxHxD): 170 x 145 x 155 mm
Weight: 1.5 kg, batteries included

Technology

- The Tester SICO 2062 FMX is suitable for acceptance/reconstruction tests and inspection and fault location in cable transmission links of the audio frequency transmission system FMX 2 / SbL 60.

- The device replaces the formerly used FMX 2-setting device.

- Selective voltage measurements allow e. g. test and setting the FMX 2 transmitter output level in which several channels can simultaneously be active.

- The device has a microcontroller. In addition to selective alternating voltage, it also measures direct voltage and frequency.

- The robust housing, wide operating temperature range and the simple, menu-assisted operation by keys and displayed information make the device especially suitable for operating and maintenance tasks.

Delivery

- Tester SICO 2062 FMX
- Carrying bag
- 2 Measuring lines with 4 mm safety plug
- 2 Test probes
- 2 Clip terminals with tongs
- 2 rechargeable batteries type C (Baby/R14)
- Manual
- Acceptance test certificate 3.1 according BS EN 10204

Optional accessories

Signal Concept GmbH
Geschäftsführer: Stefan Wetzig
Südring 11, 04416 Markkleeberg, Deutschland
Tel.: +49 (0)34297 1439 0, Fax: +49 (0)34297 1439 13

E-Mail: info@signalconcept.de
Internet: www.signalconcept.de
Umsatzsteuer-ID gemäß § 27 a Umsatzsteuergesetz: DE155914966

- Adapter for measuring operating voltage and amplifier output voltage (FMX 2-line control unit)

Signal Concept GmbH
Geschäftsführer: Stefan Wetzig
Südring 11, 04416 Markkleeberg, Deutschland
Tel.: +49 (0)34297 1439 0, Fax: +49 (0)34297 1439 13

E-Mail: info@signalconcept.de
Internet: www.signalconcept.de
Umsatzsteuer-ID gemäß § 27 a Umsatzsteuergesetz: DE155914966

Signal Concept GmbH
Geschäftsführer: Stefan Wetzig
Südring 11, 04416 Markkleeberg, Deutschland
Tel.: +49 (0)34297 1439 0, Fax: +49 (0)34297 1439 13

E-Mail: info@signalconcept.de
Internet: www.signalconcept.de
Umsatzsteuer-ID gemäß § 27 a Umsatzsteuergesetz: DE155914966